



LED BAR 144 SMD RGB

Quickstart Manual

Menu function		
Display	Range	Function
Addr	001-512	DMX address setup
Chnd	3/5/6/12/24/48ch	DMX mode select
SInd	Mast	Master
	SL1	Slave 1
	SL2	Slave 2
	d512	DMX fail - blackout
Soun	So0-So16	Sound mode select
	Se00-Se99	Sound mode sensitivity
COLO	RED 000-255 GREEN 000-255 BLUE 000-255	Color brightness control
disp		Display reversed by 180°
Ver		Firmware version
Rset		Fixture reset

Specification	
Power consumption	25 W
Supply voltage	100 - 240 V
Supply frequency	50 - 60 Hz
Diode type	RGB
Diode number	144
Strobe	do 20Hz
Display	LCD
Control	4 buttons
Dimming	Smooth 0-100%
Ilość kanałów DMX	3/5/6/12/24/48
Control	DMX, Master/Slave, Sound
Microphone	builtin
DMX IN	XLR 3-pin
DMX OUT	XLR 3-pin
Dimensions	1020 x 65 x 80 mm
Weight	1 kg

3ch	Range	Function
1	000-255	Red
2	000-255	Green
3	000-255	Blue

5ch	Range	Function
1	000-255	Red
2	000-255	Green
3	000-255	Blue
4	000-255	Dimmer
5	000	-
	001-005	Sound mode
	006-010	-
	016-255	Strobe (slow-fast)

6ch	Range	Function
1	000-255	Master dimmer
2	000-255	Strobe (slow-fast)
3	000-255	Red
4	000-255	Green
5	000-255	Blue
6	000-015	-
	016-255	Auto RGB (slow-fast)

12ch	Range	Function	Section
1	000-255	Master dimmer	1
2	000-255	Strobe (slow-fast)	
3	000-255	Red	
4	000-255	Green	
5	000-255	Blue	
6	000-015	-	2
	016-255	Auto RGB (slow-fast)	
7	000-255	Master dimmer	
8	000-255	Strobe (slow-fast)	
9	000-255	Red	
10	000-255	Green	
11	000-255	Blue	
12	000-015	-	
	016-255	Auto RGB (slow-fast)	

24ch	Range	Function	Section
1	000-255	Red	1
2	000-255	Green	
3	000-255	Blue	
4	000-255	Red	2
5	000-255	Green	
6	000-255	Blue	
7	000-255	Red	3
8	000-255	Green	
9	000-255	Blue	
10	000-255	Red	4
11	000-255	Green	
12	000-255	Blue	
13	000-255	Red	5
14	000-255	Green	
15	000-255	Blue	
16	000-255	Red	6
17	000-255	Green	
18	000-255	Blue	
19	000-255	Red	7
20	000-255	Green	
21	000-255	Blue	
22	000-255	Red	8
23	000-255	Green	
24	000-255	Blue	

48ch	Range	Function	Section
1	000-255	Master dimmer	1
2	000-255	Strobe (slow-fast)	
3	000-255	Red	
4	000-255	Green	
5	000-255	Blue	
6	000-015	-	2
	016-255	Auto RGB (slow-fast)	
7	000-255	Master dimmer	
8	000-255	Strobe (slow-fast)	
9	000-255	Red	
10	000-255	Green	3
11	000-255	Blue	
12	000-015	-	
	016-255	Auto RGB (slow-fast)	
13	000-255	Master dimmer	
14	000-255	Strobe (slow-fast)	4
15	000-255	Red	
16	000-255	Green	
17	000-255	Blue	
18	000-015	-	
	016-255	Auto RGB (slow-fast)	5
19	000-255	Master dimmer	
20	000-255	Strobe (slow-fast)	
21	000-255	Red	
22	000-255	Green	6
23	000-255	Blue	
24	000-015	-	
	016-255	Auto RGB (slow-fast)	
25	000-255	Master dimmer	
26	000-255	Strobe (slow-fast)	7
27	000-255	Red	
28	000-255	Green	
29	000-255	Blue	
30	000-015	-	
	016-255	Auto RGB (slow-fast)	8
31	000-255	Master dimmer	
32	000-255	Strobe (slow-fast)	
33	000-255	Red	
34	000-255	Green	9
35	000-255	Blue	
36	000-015	-	
	016-255	Auto RGB (slow-fast)	
37	000-255	Master dimmer	
38	000-255	Strobe (slow-fast)	10
39	000-255	Red	
40	000-255	Green	
41	000-255	Blue	
42	000-015	-	
	016-255	Auto RGB (slow-fast)	11
43	000-255	Master dimmer	
44	000-255	Strobe (slow-fast)	
45	000-255	Red	
46	000-255	Green	12
47	000-255	Blue	
48	000-015	-	
	016-255	Auto RGB (slow-fast)	