



FIX BEE EYE

Quick start manual

1. Menu functions

Display	Value	Function
d001	001-512	DMX address setup
CH05	05 / 06 / 08	DMX mode select
T 30	00-99	Actual temperature
r255	000-255	Red
G255	000-255	Green
b255	000-255	Blue
u255	000-255	White
FF99	00-99	Strobe (slow-fast)
F000	000-255	000-128: lens rotation 0-360° 129-190: Lens rotation forward (slow-fast) 191-255: Lens rotation backward (slow-fast)
CC99	00-99	Color snap (slow-fast)
DE99	00-99	Color fade (slow-fast)
SH 1	1-3	SH 1: Fast auto program 1 SH 2: Fast auto program 2 SH 3: Slow auto program
SU00	00-99	Sound sensitivity setting (low-high)

2. DMX modes

5CH	Range	Function
1	0-255	Red
2	0-255	Green
3	0-255	Blue
4	0-255	White
5	0-128 129-190 191-255	Lens indexing Lens rotation forward Lens rotation backward
6CH	Value	Function
1	0-255	Dimmer
2	0-255	Red
3	0-255	Green
4	0-255	Blue
5	0-255	White
6	0-128 129-190 191-255	Lens indexing Lens rotation forward Lens rotation backward
8CH	Zakres	Funkcja
1	0-255	Dimmer
2	0-255	Red
3	0-255	Green
4	0-255	Blue
5	0-255	White
6	000-006 007-255	Open Strone (slow-fast)
7	0-25 26-50 51-100 101-150 151-200 201-225 226-250 251-255	DMX mode Color select Color snap (slow-fast) Color fade (slow-fast) Fast auto show 1 Fast auto show 2 Slow auto show Sound sensitivity setting (low-high)
8	0-128 129-190 191-255	Lens indexing Lens rotation forward Lens rotation backward

Specification	
Power consumption	60 W
Supply voltage	220 - 240 V
Supply frequency	50 - 60 Hz
Diode type	4 in 1
Diode number	6
Diode power	10 W
Display	LED - 4 znaki
Control	4 buttons
Control modes	DMX, Auto, Master/Slave, Sound
Beam angle	25°
Dimming	Smooth 0-100%
DMX channels	5/6/8
Standard DMX	DMX512
DMX IN	XLR
DMX OUT	XLR
IP protection rating	IP20
enclosure	Metal
cooling	yes